Card Reader
LTK-R101MK

Key Features:

·Meets the standard of ISO 14443-A and the card reading frequency is 13.56MHz. The number and content of MIFARE card can be read;
·Watchdog design for repairing itself in case that exception occurs, to ensure the long service life of the reader;
·Built-in buzzer for identifying the reading status.



LTK-R101MK

Properties	
Power Supply	DC 12V
Power consumption	≤2W
Processor	32-bit
Reading Range	≥5cm
ID Settings	Setting by the DIP Switch on the Main Board
Communication Interface	RS-485/Wiegand (DIP Switch)
Audio Alert	Beeper
Keypad	Keypad with12 Keys(0~9, *, #) for LTK-R101MK
LED Indicator	Power Indicator, Status Indicator
Working Temperature	-4°F to 149°F(-20°C to +65°C)
Working Humidity	10 % to 90 % (Non-Condensing)
Dimensions	4.53"x1.73"x0.87"(115mm×44mm×22mm)
Tampering Alarm	Support
Water-proof	IP65
Installing Method	Wall mounting with screws. The Gang Box is not supported.

©2017 LT Security, Inc. All Rights Reserved. White papers, data sheets, quick start guides, and/or user manuals are for reference only and may or may not be entirely up to date or accurate based upon the version or models. Product names mentioned herein may be the unregistered and/or registered trademarks of their respective owners.